

# POWER TRANSFORMER CHASSIS MOUNT: QUICK-CONNECT WORLD SERIES $^{\text{TM}}$

## **VPS24-1000**

#### **Electrical Specifications (@25C)**

1. Maximum Power: 25VA

2. Primary - **Series:** 230VAC@50/60Hz; **Parallel:** 115VAC@50/60Hz 3. Secondary - **Series**<sup>1</sup>: 24V CT@ 1.0A; **Parallel**<sup>2</sup>: 12.0V @ 2.0A

4. Voltage Regulation: 25% TYP @ full load to no load

5. Temperature Rise: 40C TYP

6. Operating Temperature: -40°C to 70°C

7. Insulation Resistance:  $100M\Omega$ 

8. Recommended Fuse3:

Series: Littelfuse p/n 313 1.25HXP, 1.25A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-1 ¼, 1.25A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or,

Cooper Bussmann p/n BKMDL-2 ½, 2.5A 250V, ¼ x 1 ¼

#### Construction:

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safety:

These units are designed with 4000VAC isolation between the primary and secondary, and also, between each winding and the core.

### Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.

File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3

CSA: File LR 221330. C22.2 NO. 66, General Purpose.

TUV Certificate No.: R72103639, EN60950, Information Technology







A. Dimensions:						Unit: In inches		
Н	W	D	Α	В	С	Т	MW	ML
2-5/16	2-13/16	1-15/16	2	1-1/8	5/16	3/16	2-3/8	-

B. Mounting Hole Size: 3/16"

C. WT Lbs. : 1.25

D. Terminal Size: 0.187"x 0.020"

#### Connections<sup>4</sup>:

Input: Series - 6 and 1, Jumper 5 to 2

Parallel - 6 and 1, Jumper 6 to 2 and 5 to 1

Output: Series - 12 and 7, Jumper 11 to 8

Parallel - 12 and 7, Jumper 12 to 8 and 11 to 7

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


<sup>&</sup>lt;sup>4</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.




460 Harley Knox Blvd. Perris. California 92571









Publish Date: September 6, 2017

<sup>&</sup>lt;sup>1</sup> Non-Inherently limited. Class 3.

<sup>&</sup>lt;sup>2</sup> Non-Inherently limited. Class 2 not wet, Class 3 wet.

<sup>&</sup>lt;sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.