



## At a glance

- Modular design
- 4 m, 5.5 m or 7 m protective field range
- Up to 21 switchable field sets (21 protective fields, 42 warning fields)
- EFI interface for safe SICK device communication
- Selectable resolution for hand, leg or body detection
- Configuration memory integrated in the system plug
- Direct integration in PROFINET IO safe bus system
- Incremental encoder inputs for speed-dependent field switching

## Your benefits

- Tailored solutions for your applications
- Easy installation, commissioning and maintenance for stationary and mobile applications
- Largest protective field range available in the market increases the variety of application possibilities
- Variety of field sets ensures safety and productivity when protecting vehicles or moving machine parts
- Easily expandable modular system, simple cabling and additional functions using SICK safety controllers with EFI
- Quick recommissioning via configuration memory
- Decades of proven safety technology guarantee maximum reliability and productivity – even under difficult conditions

## Ordering information

See [www.mysick.com/products](http://www.mysick.com/products) for additional accessories

## S3000 variants

| Variant            | Field sets          | Protective field range | Model name  | Part no. |
|--------------------|---------------------|------------------------|-------------|----------|
| S3000 Standard     | 1                   | 4 m                    | S30A-4011BA | 1028934  |
|                    |                     | 5.5 m                  | S30A-6011BA | 1023546  |
|                    |                     | 7 m                    | S30A-7011BA | 1023890  |
| S3000 Advanced     | 4                   | 4 m                    | S30A-4011CA | 1028935  |
|                    |                     | 5.5 m                  | S30A-6011CA | 1023547  |
|                    |                     | 7 m                    | S30A-7011CA | 1023891  |
| S3000 Professional | 8                   | 4 m                    | S30A-4011DA | 1028936  |
|                    |                     | 5.5 m                  | S30A-6011DA | 1019600  |
|                    |                     | 7 m                    | S30A-7011DA | 1023892  |
| S3000 Expert       | 21/32 <sup>1)</sup> | 4 m                    | S30A-4011GB | 1052107  |
|                    |                     | 5.5 m                  | S30A-6011GB | 1052108  |
|                    |                     | 7 m                    | S30A-7011GB | 1052109  |
| S3000 Remote       | 21/32 <sup>1)</sup> | 4 m                    | S30A-4011EA | 1028938  |
|                    |                     | 5.5 m                  | S30A-6011EA | 1023548  |
|                    |                     | 7 m                    | S30A-7011EA | 1023893  |
| S3000 Cold Store   | 4                   | 7 m                    | S31A-7011CA | 1041648  |

<sup>1)</sup> Triple field mode/dual field mode.

| Variant                        | Field sets | Connection type   | Protective field range | Model name  | Part no. |
|--------------------------------|------------|---|------------------------|-------------|----------|
| S3000 PROFINET IO Advanced     | 4          | 2 bushes for RJ45 push-pull plug for copper lines       | 4 m                    | S30A-4111CP | 1045650  |
|                                |            |   | 5.5 m                  | S30A-6111CP | 1045652  |
|                                |            |   | 7 m                    | S30A-7111CP | 1045654  |
|                                |            | 2 bushes for SCRJ push-pull plug for fiber optic cables | 4 m                    | S30A-4111CL | 1052591  |
|                                |            |   | 5.5 m                  | S30A-6111CL | 1052593  |
|                                |            |   | 7 m                    | S30A-7111CL | 1052595  |
| S3000 PROFINET IO Professional | 8          | 2 bushes for RJ45 push-pull plug for copper lines       | 4 m                    | S30A-4111DP | 1045651  |
|                                |            |   | 5.5 m                  | S30A-6111DP | 1045653  |
|                                |            |   | 7 m                    | S30A-7111DP | 1045655  |
|                                |            | 2 bushes for SCRJ push-pull plug for fiber optic cables | 4 m                    | S30A-4111DL | 1052592  |
|                                |            |   | 5.5 m                  | S30A-6111DL | 1052594  |
|                                |            |   | 7 m                    | S30A-7111DL | 1052596  |

### Accessories required for commissioning

| Description  | Number                 |                |                |                    |              |              |                            |                                |                  |
|--|------------------------|----------------|----------------|--------------------|--------------|--------------|----------------------------|--------------------------------|------------------|
|  |                        | S3000 Standard | S3000 Advanced | S3000 Professional | S3000 Expert | S3000 Remote | S3000 PROFINET IO Advanced | S3000 PROFINET IO Professional | S3000 Cold Store |
| Mounting kit   | 1                      | ●              | ●              | ●                  | ●            | ●            | ●                          | ●                              | -                |
| Adjustment bracket (specially for Cold Store)                                | 1                      | -              | -              | -                  | -            | -            | -                          | -                              | ●                |
| System plug  | 1 <sup>1)</sup>        | ●              | ●              | ●                  | ●            | ●            | -                          | -                              | -                |
| Power supply plug (PROFINET IO)  | 1                      | -              | -              | -                  | -            | -            | ●                          | ●                              | -                |
| Service cable for configuration and diagnostics                              | Can be used repeatedly | ●              | ●              | ●                  | ●            | ●            | -                          | -                              | -                |
| Service cable (configuration cable) <sup>2)</sup> (specially for Cold Store) | 1                      | -              | -              | -                  | -            | -            | -                          | -                              | ●                |
| CDS (configuration and diagnostic software) <sup>3)</sup>                    | Can be used repeatedly | ●              | ●              | ●                  | ●            | ●            | ●                          | ●                              | ●                |

<sup>1)</sup> If system plugs without cables are used, an additional connecting cable is required.





<sup>2)</sup> See "Recommended accessories for S3000 Cold Store", page 37.

<sup>3)</sup> Included in delivery if a device variant is ordered.

## Recommended accessories S3000



See [www.mysick.com/products](http://www.mysick.com/products) for further accessories

### Mounting bracket/plates



| Figure  | Description   | Model name                  | Part no. |
|---|---|-----------------------------|----------|
|  | Mounting bracket for direct mounting at the rear of the wall or machine. No adjustment option.  | Mounting kit 1              | 2015623  |
|  | Bracket only in conjunction with mounting kit 1. Mounting at rear of the wall or machine. Adjustment by longitudinal and lateral axis possible.   | Mounting kit 2              | 2015624  |
|  | Bracket only in conjunction with mounting kit 1 and 2. Mounting on the wall at the rear or at the base at the wall, floor or machine. Adjustment by longitudinal and lateral axis possible. | Mounting kit 3              | 2015625  |
|  | Mounting bracket, heavy version, with protective hood, steel, painted, for floor mounting, height adjustment possible.  | Heavy-duty mounting bracket | 7087514  |

### Plug connectors and cables





#### System plugs without cables

| Figure   | Description   | Model name  | Part no. |
|--|---|-------------|----------|
|   | For S3000 Standard, Advanced, Remote, Professional and Expert (not for use with incremental encoders) | SX0A-A0000B | 2023797  |
|  | For S3000 Professional and Expert (for use with incremental encoders)                                 | SX0A-A0000D | 2023310  |

#### System plugs pre-assembled


| Figure  | Description   | Length of cable | Model name  | Part no. |
|---|---|-----------------|-------------|----------|
|  | For S3000 Standard and Remote   | 5 m             | SX0A-B0905B | 2027170  |
|   | For S3000 Standard and Remote, cable outlet at rear                       | 5 m             | SX0A-B0905G | 2049222  |
|   | For S3000 Standard and Remote   | 10 m            | SX0A-B0910B | 2027171  |
|   | For S3000 Standard and Remote   | 20 m            | SX0A-B0920B | 2027814  |
|   | For S3000 Advanced  | 5 m             | SX0A-B1305B | 2027172  |
|   | For S3000 Advanced  | 10 m            | SX0A-B1310B | 2027173  |
|   | For S3000 Advanced  | 20 m            | SX0A-B1320B | 2027815  |
|   | For S3000 Professional and Expert (not for use with incremental encoders) | 5 m             | SX0A-B1705B | 2027174  |
|   | For S3000 Professional and Expert (not for use with incremental encoders) | 10 m            | SX0A-B1710B | 2027175  |
|  | For S3000 Professional and Expert (not for use with incremental encoders) | 20 m            | SX0A-B1720B | 2027816  |
|   | For S3000 Professional and Expert (for use with incremental encoders)     | 5 m             | SX0A-B1305D | 2027176  |
|   | For S3000 Professional and Expert (for use with incremental encoders)     | 10 m            | SX0A-B1310D | 2027177  |

**System plug (PROFINET IO)**


| Figure  | Description  | Length of cable | Model name    | Part no. |
|---|--|-----------------|---------------|----------|
|  | For S3000 PROFINET IO Advanced and Professional  | -               | SX1A-A0000L   | 2047286  |
|  | For S3000 PROFINET IO Advanced and Professional  | 1 m             | SX1A-B0201L   | 2049575  |
|  | Power-Y distributor with power supply plug for S3000 PROFINET IO Advanced and Professional | -               | SX1A-B0201M   | 2049857  |
|  | Adapter cable, RJ45/M12  | -               | Adapter cable | 6044052  |

Additional accessories for PROFINET connection technology, e.g., **RJ-45 or SCRJ push-pull connection plug**, see [www.phoenixcontact.de](http://www.phoenixcontact.de).


**Other accessories****Spare parts set for front screen**

| Figure  | Description                             | Model name | Part no. |
|---|---|------------|----------|
|  | Front screen with spare seal and screws | -          | 2027180  |



**Recommended accessories for S3000 Cold Store****Mounting bracket/plates**

| Figure  | Description  | Model name         | Part no. |
|---|--|--------------------|----------|
|  | Adjustment bracket for wall mounting, metal, weight approx. 1.6 kg (including mounting material) | Adjustment bracket | 2018303  |

**Other accessories**

| Figure  | Description                   | Model name             | Part no. |
|---|-------------------------------|------------------------|----------|
|  | With screw threads, M36 x 1.5 | Drying agent cartridge | 5306179  |

**Plug connectors and cables**

| Figure  | Description  | Model name      | Part no. |
|---|--|-----------------|----------|
|  | 16-pin connection plug, complete with housing              | Connection plug | 2018301  |
|  | Pre-assembled to RS-232. For inclusion in existing wiring. | Service cable   | 2019561  |

For general accessories, see page 50.



For enhanced system solutions, see page 51.