

Datasheet

Multiple Output Linear

D.C. Power Supply

Stock No. : Model :

1225035 **RPE-4323**

1225036 **RPE-3323**

1225037 **RPE-2323**

1225038 **RPE-1326**



FEATURES

- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 100mV/10mA (*1)
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal




The RPE-X323 series is cutting edge, economical linear DC Power supplies. The RPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for RPE-3323), high resolution, low noise, high reliability, and compact size.

The RPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the RPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters.

Additionally, output key light facilitates users in clearly reading the operational status of power supply.

A. TRACKING SERIES AND PARALLEL OPERATION



Internal connection for tracking Series and Parallel operation via control panel

In addition to independent output channels, the RPE-X323 series provides tracking series and parallel operation (For RPE-2323/RPE-3323/RPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).


B. CONVENIENT FUNCTION



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

The RPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing Voltage/Current parameters.

C. REMOTE I/O FOR OUTPUT ON/OFF FUNCTION



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.

The RPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



SPECIFICATIONS

OUTPUT MODE	Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current	RPE-4323				RPE-3323			RPE-2323		RPE-1326
		CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
		0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	5V	0~32V	0~32V	0~32V
		0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
		0~64V		-		0~64V		-		0~64V	
		0~6A		-		0~6A		-		0~6A	
CONSTANT VOLTAGE OPERATION	Line Regulation Load Regulation Ripple & Noise Recovery Time	$\leq 0.01\%+3mV$ $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) $\leq 1mV_{rms}$ (5Hz~1MHz) $\leq 100\mu s$ (50% Load Change, minimum load 0.5A)									
CONSTANT CURRENT OPERATION	Line Regulation Load Regulation Ripple & Noise	$\leq 0.2\%+3mA$ $\leq 0.2\%+3mA$ $\leq 3mArms$									
TRACKING OPERATION (CH1,CH2)	Tracking Error Parallel Regulation Series Regulation Ripple & Noise	$\leq 0.1\%+10mV$ of Master(0~32V) No Load , with Load add load regulation $\leq 100mV$ Line : $\leq 0.01\%+3mV$ Load : $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) Line : $\leq 0.01\%+5mV$ Load : $\leq 100mV$									
CH3 OPERATION FOR (GPE-3323)	Output Voltage Output Current Line Regulation Load Regulation Ripple & Noise	5.0V, $\pm 5\%$ 5A $\leq 3mV$ $\leq 5mV$ 1mV _{rms} (5Hz~1MHz)									
METER	Voltage Resolution Current Resolution Setting Accuracy Readback Accuracy	100mV (*1) 10mA (*1) Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA) Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA)									
INSULATION	Chassis and Terminal Chassis and AC Cord	20M Ω or above (DC 500V) 30M Ω or above (DC 500V)									
ENVIRONMENT CONDITION	Operation Temp Storage Temp Operating Humidity Storage Humidity	0~40 $^{\circ}C$ -10~70 $^{\circ}C$ $\leq 80\%$ RH $\leq 70\%$ RH									
OTHER	Power Source Dimensions & Weight	AC100V/120V/220V $\pm 10\%$; 230V(+10%~-6%); 50/60Hz 210(W)x 155(H) x 306(D) mm ; Approx. 7kg									

Note : (*1) For a higher resolution (10mV/1mA), please follow the setting procedure of the user manual.
When using a higher resolution, the current or voltage adjustment may be limited by the knob sensibility.

Specifications subject to change without notice.

ORDERING INFORMATION

RPE-1326 Single Channel, 192W Linear DC Power Supply
 RPE-2323 2 Channels, 192W Linear DC Power Supply
 RPE-3323 3 Channels, 217W Linear DC Power Supply
 RPE-4323 4 Channels, 212W Linear DC Power Supply

ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1
 RPE-1326 Test Lead GTL-104A x 1; GTL-105 x 1 ; or European GTL-204A x 1, GTL-203A x1
 RPE-2323 Test Lead GTL-104A x 2; or European GTL-204A x 2
 RPE-3323 Test Lead GTL-104A x 3; or European GTL-204A x 3
 RPE-4323 Test Lead GTL-104A x 2; GTL-105A x 2 or European GTL-204A x 2, GTL-203A x 2



P. O. Box 99
 Corby
 Northants NN17 9RS
 England
 Tel: +44(0) 1536 201234