

PRODUCT-DETAILS

# E 92/32

## E 92/32 Fuse switch disconnecter



### General Information

|                       |  |
|-----------------------|--|
| Extended Product Type | E 92/32  |
| Product ID            | 2CSM200883R1801  |
| EAN                   | 8012542008835  |
| Catalog Description   | E 92/32 Fuse switch disconnecter   |
| Long Description      | E 92/32 is a fuseholder for overcurrent and short circuit protection. No blown fuse indicator. |

### Ordering

|                        |               |
|------------------------|---------------|
| E-Number (Sweden)      | 2318051       |
| EAN                    | 8012542008835 |
| Minimum Order Quantity | 1 piece       |
| Customs Tariff Number  | 85361010      |

### Dimensions

|                            |          |
|----------------------------|----------|
| Product Net Width          | 0.035 m  |
| Product Net Height         | 0.085 m  |
| Product Net Depth / Length | 0.064 m  |
| Product Net Weight         | 0.132 kg |

---

**Container Information**


---

|                                |               |
|--------------------------------|---------------|
| Package Level 1 Units          | 3 piece       |
| Package Level 1 Width          | 0.105 m       |
| Package Level 1 Height         | 0.085 m       |
| Package Level 1 Depth / Length | 0.064 m       |
| Package Level 1 Gross Weight   | 0.369 kg      |
| Package Level 1 EAN            | 8012542008842 |

---



---

**Environmental**


---

|             |                                   |
|-------------|-----------------------------------|
| RoHS Status | Following EU Directive 2011/65/EU |
|-------------|-----------------------------------|

---



---

**Additional Information**


---

|                           |  |
|---------------------------|--|
| Degree of Protection      | IP20                                       |
| Dimensions                | 1 module                                   |
| Fuse Size                 | 10x38 mm                                   |
| Mounting Type             | DIN rail                                   |
| Number of Poles           | 2  |
| Number of Protected Poles | 2  |
| Options Provided          | No   |
| Power Loss                | at Rated Operating Conditions per Pole 3 W |
| Product Main Type         | E 90                                       |
| Product Name              | Fuse switch disconnecter                   |
| Rated Current ( $I_n$ )   | 32 A                                       |
| Rated Frequency (f)       | 50...60 Hz                                 |
| Rated Voltage ( $U_r$ )   | 690 V                                      |
| Rated Operational Voltage | 690 V AC                                   |
| RoHS Date                 | 41640                                      |
| Voltage Range             | 690 V AC                                   |

---



---

**Certificates and Declarations (Document Number)**


---

|                                   |                      |
|-----------------------------------|----------------------|
| Data Sheet, Technical Information | 2CSC444002B0204      |
| Declaration of Conformity - CE    | 2CSC444002D2701      |
| Environmental Information         | See RoHS Information |
| Instructions and Manuals          | on the product body  |
| RoHS Information                  | 2CSC444011K2701      |

---



---

**Classifications**


---

|                            |  |
|----------------------------|--|
| ETIM 4                     | EC000036 - Miniature fuse holder                           |
| ETIM 5                     | EC000036 - Miniature fuse holder                           |
| ETIM 6                     | EC002705 - Holder for cylindrical fuse                     |
| ETIM 7                     | EC002705 - Holder for cylindrical fuse                     |
| Object Classification Code | F  |
| WEEE Category              | 5. Small Equipment (No External Dimension More Than 50 cm) |

---

---

## Categories

---

Low Voltage Products and Systems → Modular DIN Rail Products → Protection and Safety devices → Cylindrical Fuse Holders and Fuse Switch Disconnectors

