

Current Sensor HCMR 1000A-S-50-SB5-NF



Image is for illustration purposes only. Please refer to product description.

Part number	20 31 100 8101
Specification	Current Sensor HCMR 1000A-S-50-SB5-NF
HARTING eCatalogue	https://b2b.harting.com/20311008101

Identification

Series	HCMR
Element	Current sensor
Sensor technology	Hall-Effekt Closed loop
Features	<ul style="list-style-type: none"> Hall effect compensated current sensor Measurable currents: AC, DC, pulsed, mixed ... High accuracy over the entire measuring range Galvanic insulation between primary and secondary current Internal screen between primary and secondary circuit Switchboard mounting Housing material and potting mass have a flammability rating UL 94 V-0 Applications: frequency converters, electrical drives, auxiliary converters

Version

Field of application	Railway version
Termination	4x screw lock with Faston (6.3 x 0.8 mm)

Technical characteristics

I_{PN} Nominal primary current	1,000 A
I_{PM} Primary current, measuring range	0 ... $\pm 2,400$ A
R_M Measuring resistance @ $I_{PM \max}$, $U_C \max$, $T_A \max$	2 Ω For other primary currents see diagram.
I_{SN} Nominal secondary current	200 mA
K_N Turns ratio	1 : 5000
U_C Power supply	± 15 ... ± 24 V ± 5 %



Pushing Performance

Technical characteristics

I_C Current consumption @ $U_{C \min}$	20 mA + I_S
X Overall accuracy @ I_{PN} , $T_A = 25^\circ\text{C}$	$\pm 0.4\%$
E_L Linearity	$< 0.1\%$
I_O Offset current @ $I_P = 0\text{ A}$, $T_A = 25^\circ\text{C}$	$\pm 0.5\text{ mA}$
I_{OT} maximum temperature drift of I_O	$\pm 0.8\text{ mA}$
t_r Response time @ I_{PN}	$< 1\ \mu\text{s}$
di/dt with optimal coupling	$> 100\text{ A}/\mu\text{s}$
f Frequency	0 ... 100 kHz
T_A Ambient temperature	$-40 \dots +85^\circ\text{C}$
T_S Storage temperature	$-45 \dots +90^\circ\text{C}$
R_S Secondary coil resistance @ $T_{A \max}$	44 Ω
U_D Test voltage, effective (50 Hz, 1 min)	12 kV Primary - secondary 1 kV Secondary - screen
U_{St} Rated impulse voltage (1,2/50 μs)	20 kV
U_B Rated voltage	2,000 V
Overvoltage category	III
Pollution degree	2
L_S Clearance distance	50 mm
K_S Creepage distance	50.5 mm
Tightening torque	4 Nm (4x steel screw M5 - Vertical)

Material properties

Material (hood/housing)	Polycarbonate (PC)
Material flammability class acc. to UL 94	V-0
RoHS	compliant with exemption
RoHS exemptions	6(a) / 6(a)-I: Lead as an alloying element in steel for machining purposes and in galvanised steel containing up to 0,35 % lead by weight / Lead as an alloying element in steel for machining purposes containing up to 0,35 % lead by weight and in batch hot dip galvanised steel components containing up to 0,2 % lead by weight
ELV status	compliant with exemption
China RoHS	50



Pushing Performance

Material properties

REACH Annex XVII substances	No
REACH ANNEX XIV substances	No
REACH SVHC substances	Yes
REACH SVHC substances	Lead


Specifications and approvals

Specifications	EN 50155 IEC 61373
Approvals	DNV GL
UL / CSA	UL 508 NMTR2.E359667 CSA-C22.2 No. 14-13 NMTR8.E359667
CE	Yes

Commercial data

Packaging size	1
Net weight	945 g
Country of origin	Germany
European customs tariff number	90303370
eCl@ss	27210902 Current transformer

Measuring resistance



— $U_C = \pm 24 \text{ V} -5 \%$, $T_A = 85 \text{ °C}$

- - - $U_C = \pm 15 \text{ V} -5 \%$, $T_A = 85 \text{ °C}$

Primary currents higher than I_{PM} only for peak!

Remark

- If I_P flows in the direction of the arrow I_S is positive.
- Over currents ($\gg I_{PN}$) or the missing of the supply voltage can cause an additional permanent magnetic offset.
- The temperature of the primary conductor may not exceed 100 °C .



Pushing Performance

Safety note



These transformers may only be used in electrical or power electronic applications which fulfill the relevant regulations (standards, EMC requirements,...).

Caution, risk of electric shock



- Pay attention to protect non-insulated high-power current carrying parts against direct contact (e.g. with a protective enclosure).
- When installing this sensor please make sure that the safe separation (between primary circuit and secondary circuit) is maintained over the whole circuits and their connections.
- The sensor may only be connected to a power supply respecting the SELV/PELV protective regulations according to EN 50 178. The installation of the power supply must be short-circuit-proof.
- Disconnecting the main power must be possible.
- The current sensors support a safe separation. The creepage and clearance distances are taken as a basis for the rated voltage. They are the shortest distance between the secondary connection and the sensor's window. The actual clearance and creepage distances depend on the position of the primary conductor respectively on the actual shortest distance between the primary conductor and the secondary connection.