

# Product data sheet

## Characteristics

# TCSMCN1M1F1

Modbus shielded cable - M12 male connector - M12 female connector - IP67 - 1 m

Product availability: Non-Stock - Not normally stocked in distribution facility



### Main

Range of product	OsiSense XG
Accessory / separate part category	Connection accessories
Accessory / separate part type	Connecting cable
Accessory / separate part designation	Modbus shielded connecting cable
Accessory / separate part destination	Tap-off box Compact station
Cable length	3.28 ft (1 m)

### Complementary

Electrical connection	1 female connector M12 straight A coding 1 male connector M12 straight A coding
Color	Black
Net weight	0.18 lb(US) (0.08 kg)

### Environment

IP degree of protection	IP67
-------------------------	------

### Ordering and shipping details

Category	22490 - SENSORS-ULTRASONIC (XX5,6)
Discount Schedule	DS2
GTIN	03389119018456
Package weight(Lbs)	0.10 kg (0.21 lb(US))
Returnability	No
Country of origin	PL

### Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Di-isodecyl phthalate (DIDP) and Diisononyl phthalate (DINP) which is known to the State of California to cause Carcinogen and Reproductive harm. For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) <a href="#">EU RoHS Declaration</a>
Mercury free	Yes
RoHS exemption information	<a href="#">Yes</a>

### Contractual warranty

Warranty	18 months
----------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.