

Dual Monitor USB C Docking Station with 60W Power Delivery for Windows Laptops - USB C to HDMI or DVI Dock - USB 3.1 Gen 1 Type C Dock w/ Charging - Thunderbolt 3 Compatible

Product ID: MST30C2HHPD



Enhance your productivity by turning your Windows® USB-C™ laptop into a full-scale workstation. This dual-monitor USB-C dock lets you easily connect two HDMI monitors or DVI monitors (with included adapters) using one USB-C cable, with no setup of display drivers required right out of the box. The USB-C dock provides 60W charging power, and five USB 3.0 ports to connect devices. With easy dual-monitor setup, the dock is ideal for wide-scale use in office workstations.

Create a Dual-Monitor Workstation

The USB-C dock lets you connect dual monitors with flexible options. Connect to:

- 2x HDMI or 2x DVI displays at 1920 x 1200p @ 60Hz
- 1x HDMI + 1x DVI display

You can also connect a single 4K HDMI display.

Connect More Devices

Unlike some USB-C docks that may drop to USB 2.0 and limit Ethernet performance, this USB Type-C™ dock offers full USB 3.0 and network bandwidth. This provides faster data transfer speeds when using your USB 3.0 peripherals and supports true Gigabit Ethernet network throughput.

This USB Type-C docking station gives you five USB 3.0 ports (1x USB-C and 4x USB-A including 1x Fast-Charge), a Gigabit Ethernet port (PXE Boot support), plus audio and microphone connections.

60W Charging Power

The USB-C docking station with Power Delivery will power and charge (up to 60W) your laptop, while powering your devices.

Fast, Easy Setup

The dock features automatic driver installation for easy setup. It works with Windows based laptops with a USB-C port that supports DP Alt Mode and USB Power Delivery.

Connected Device Transparency with the StarTech.com MAC Address Changer Utility

the MST30C2HHPD, includes a free Windows® application that enables you to better manage your enterprise network security. When you connect to your network through the ethernet port of the DK30CHHPD, the computer's MAC address is typically not broadcast to the network, as your network only sees the MAC address of the docking station. However, the StarTech.com MAC Address Changer or Cloning software enables the USB-C dock to use MAC address spoofing of the connected Windows laptop rather than the MAC address of the dock itself. This ensures your network administrators have full visibility of each device on the network and can monitor and limit activity accordingly. To request access to our MAC Address Changer utility, please contact our Technical Support Department by phone, [live chat](#), or [e-mail](#).

The MST30C2HHPD is backed by a StarTech.com 3-year warranty and free lifetime technical support.

Notes:

- *Ensure your laptop's drivers, firmware, and operating system are current prior to using the docking station.*
- *Video output capabilities depend on the video card and hardware specifications of the connected laptop.*
- *Not all USB-C ports support the full functionality of the USB Type-C standard. Ensure that your laptop's USB-C port supports DP Alt Mode and USB Power Delivery for the full functionality of the USB Type-C standard.*
- *Not all Thunderbolt 3 USB-C ports support the full functionality of the Thunderbolt 3 standard. Ensure that*

your laptop Thunderbolt 3 port supports USB Power Delivery.

Certifications, Reports and Compatibility



Applications

- Add essential ports required for mass deployment in an office environment
- Ideal for USB-C equipped Windows laptops such as Dell XPS™, Lenovo® ThinkPad™, HP® Spectre, HP EliteBook and HP ProBook

Features

- FULL FEATURE USB-C DOCK: USB 3.1 Gen 1 5Gbps type-c docking station with dual monitor 1080p HDMI or DVI, 4x USB-A (incl. 1 front fast charge), 1x USB-C, 60W PD, Gigabit Ethernet & 3.5mm headset audio
- NEW & EXISTING MONITOR SUPPORT: Dual monitor USB-C dock offers flexible setup w/ support for multiple video output combinations: dual HDMI, HDMI + DVI & Dual DVI w/ incl. HDMI to DVI display adapters
- WIDE DEVICE COMPATIBILITY: This USB Type-C MST (Multi Stream Transport) docking station is compatible with Windows USB-C and Thunderbolt 3 (TB3) laptops incl. HP, Lenovo, Dell and Microsoft Surface
- EASY TO SET UP & MANAGE: The plug and play USB-C laptop dock has automatic driver installation, 2x HDMI to DVI adapters, 1m/3.3ft. host cable, front facing power button, MAC Address Changer Utility
- 60W POWER DELIVERY & CHARGING: This USB-C port replicator with 60W PD powers & charges ultrathin laptops & ultrabooks like Lenovo ThinkPad X1 Carbon, Dell XPS 13, HP EliteBook, Microsoft Surface Pro 7

Hardware	Warranty	3 Years	
	4K Support	Yes	
	Bus Type	USB-C	
	Chipset ID	VIA/VLI - VL813 MegaChips - STDP4320 Realtek - RTL8153 C-Media - CM6533 Texas Instruments - TPS65983	
	Displays Supported	2	
	Fast-Charge Port(s)	Yes	
	Industry Standards	USB Power Delivery Specification Rev. 2.0 USB Battery Charging Specification Rev. 1.2 DisplayPort 1.2 with MST IEEE 802.3, IEEE 802.3u, IEEE 802.3ab USB 3.0 - Backward compatible with USB 2.0 and 1.1	
Performance	Auto MDIX	Yes	
	Compatible Networks	10/100/1000 Mbps	
	Full Duplex Support	Yes	
	Maximum Data Transfer Rate	5 Gbps (USB 3.0) 2 Gbps (Ethernet; Full-Duplex)	
	Maximum Digital Resolutions	1920 x 1200p @ 60Hz (HDMI/DVI - Dual Monitors) 4096 x 2160p @ 24Hz (HDMI - Single Monitor) 3840 x 2160p @ 30Hz (HDMI - Single Monitor) 1920 x 1200p @ 60Hz (DVI - Single Monitor)	
	PXE	Yes	
	Type and Rate	USB 3.0 - 5 Gbit/s	
	UASP Support	Yes	
Connector(s)	Connector Type(s)	2 - USB Type-C (24 pin) USB 3.0 (5Gbps) Female 2 - HDMI (19 pin) Female 1 - USB 3.0 A (Fast-Charge, 9 pin) Female 3 - USB Type-A (9 pin) USB 3.0 Female 1 - RJ-45 Female 1 - 3.5 mm Mini-Jack (4 Position) Female	
	Software	OS Compatibility	Windows® 7, 8, 8.1, 10
	Special Notes / Requirements	Note	Ensure your laptop's drivers, firmware, and operating system are up to date prior to using the docking station.

For a dual-monitor configuration, the Windows laptop must support MST.

A 4K-capable HDMI display is required to achieve 4K resolution

Video output capabilities are dependent on the video card and hardware specification of your connected laptop.

Not all USB-C ports support the full functionality of the USB Type-C standard. Ensure that your laptop USB-C port supports DP Alt Mode, as well as USB Power Delivery.

USB 3.0 is also known as USB 3.1 Gen 1; this connectivity standard offers speeds up to 5Gbps

Not all Thunderbolt 3 USB-C ports support the full functionality of the Thunderbolt 3 standard. Ensure that your laptop Thunderbolt 3 port supports USB Power Delivery.

This docking station provides up to 60W of Power Delivery to charge your laptop. Some laptops may have specific charging requirements such as the full 60W for charging. In the event that your laptop is not charging, simply unplug any peripheral accessories attached to the dock's USB-C port (on back of dock) and the USB 3.0 (Type-A) charging port (on front of dock) during charging. This will ensure the full 60 W of power is available for charging your laptop.

System and Cable Requirements

A Windows-based laptop with an available USB-C port (to ensure full adapter functionality, the host USB-C port must support USB Power Delivery 2.0 and DP Alt Mode)

Power

Center Tip Polarity	Positive
Input Current	2 A
Input Voltage	100 - 240 AC
Output Current	5 A
Output Voltage	20V DC
Plug Type	N
Power Consumption (In Watts)	100 W
Power Delivery	60W
Power Source	AC Adapter Included

Environmental

Humidity	5%~95% RH (Non-condensing)
Operating Temperature	0°C to 40°C (32°F to 104°F)
Storage Temperature	-20°C to 70°C (-4°F to 158°F)

Physical Characteristics	Color	Black
	Material	Plastic
	Product Height	0.9 in [2.4 cm]
	Product Length	8.7 in [22 cm]
	Product Width	3.1 in [80 mm]
	Weight of Product	9.1 oz [258 g]
Packaging Information	Package Height	3.5 in [90 mm]
	Package Length	6.2 in [15.8 cm]
	Package Width	10.4 in [26.5 cm]
	Shipping (Package) Weight	3.1 lb [1.4 kg]
What's in the Box	Included in Package	1 - docking station
		1 - 1m USB-C to USB-C cable
		2 - HDMI to DVI adapters
		1 - universal power adapter (NA/JP, ANZ)
		1 - quick-start guide

Product appearance and specifications are subject to change without notice.