





## **Datasheet**

## RS Pro Power Inverter Pure Sine Wave 12V 3000W

Stock number: 72239619





## **Specifications:**

Model	72239619
Rated power	3000W
Surge power	6000W
Output voltage	110V
Output frequency	60Hz±3
Output waveform	Pure sine wave
Low voltage alarm	12V±0.5V DC
Low voltage shutdown	10.5V±0.5V DC
Low voltage automatic restart	11.8V±0.5V DC
Overvoltage shutdown	15V $\pm$ 0.5V DC
USB port	5V 2.1A
Input voltage	12V
Dimension (LxWxH)	488x230x108mm
N.W/unit	7710g

## Features:

- Anodized aluminum case provides durability & max heat dissipation
- Two LED indicators on the front panel shows the working and failure state
- ON/OFF switch control the inverter by hand
- The inverter is compact, light weight and east to operate.
- Protections: overheat, overload, low-voltage alarm & shutdown, over-voltage, short circuit, reverse polarity
- Soft start
- · Auto. Reset after being in protected
- · USA output socket.

