Axial Lead & Cartridge Fuses 3AB > Fast-Acting > 505 Series

505 Series, Lead-free 3AB, Fast-Acting Fuse











Agency Approvals					
Agency	Agency File Number	Ampere Range			
c FL °us	E10480	10A - 30A			
\bigcirc	1620079	10A - 12A			
A	T5026910801	15A - 30A			
(E	N/A	10A - 30A			

Description

A 500VAC/VDC rated ceramic fuse with a 20,000 interrupting rating in a compact 6.3 x 32mm package, which is well suited for circuit protection in high energy applications.

Features

- In accordance with Underwriters Laboratories Standard UL 248-14
- · Available in cartridge and axial lead form and with various lead forming dimensions.
- RoHS compliant and Lead-free
- Interrupting rating of 20,000 Amperes
- · Compact form factor of 6.3mm x 32mm

Applications

- Uninterruptible Power Supplies (UPS)
- Three-Phase Power Supplies

Electrical Characteristics for Series

% of Ampere Rating	Ampere Rating	Opening Time
150%		30 minutes, Maximum
200%	10A - 30A	30 minutes, Maximum
300%		10 seconds, Maximum

Additional Information







Resources



Samples



Accessories

For recommended fuse accessories for this product series, see 'Recommended Accessories' section.

Electrical Characteristic Specifications by Item


	Ampere	Voltage	Interrupting	Nominal Cold	Nominal	Agency Approvals			
Amp Code	Rating (A)	Rating (V)	Rating	Resistance (Ohms)	Melting I²t (A² sec)	c 'AL ° us	\bigcirc	<u></u>	Œ
010.	10	450	20kA@450VAC 1000A@250VDC	0.0167	91	х	Х	-	Х
010.*	10	500	200A@500VAC 200A@500VDC	0.0167	91	х	-	-	х
012.	12	450	20kA@450VAC 1000A@250VDC	0.0117	192	x	х	-	х
015.	15	500	50kA@500VAC	0.0073	68	Х	-	Х	Х
016.	16	500	20kA@500VDC	0.0073	68	Х	-	Х	Х
020.	20	500		0.0056	140	Х	-	Х	Х
025.	25	500	30kA@500VAC 20kA@500VDC	0.0048	210	Х	-	Х	Х
030.	30	500		0.0038	280	×	-	×	X

Notes

- 1. 20kA @ 500VAC and 20kA @ 500VDC interrupting rating available for TUV certification of 15A 30A
- 2. *200A @ 500VAC and 200A @ 500VDC interrupting rating available for 10A. Add suffix "500". Example: 0505010.MX500P, and 0505010.MX500P.




Temperature Re-rating Curve




Note:

Rerating depicted in this curve is in addition to the standard derating of 25% for continuous operation.

Average Time Current Curves



Soldering Parameters - Wave Soldering



Recommended Process Parameters:

Wave Parameter	Lead-Free Recommendation		
Preheat:			
(Depends on Flux Activation Temperature)	(Typical Industry Recommendation)		
Temperature Minimum:	100° C		
Temperature Maximum:	150°C		
Preheat Time:	60-180 seconds		
Solder Pot Temperature:	270°C		
Solder DwellTime:	10 seconds Maximum		

Recommended Hand-Solder Parameters:

Solder Iron Temperature: 350°C +/- 5°C

Heating Time: 5 seconds max.

Note: These devices are not recommended for IR or Convection Reflow process.

Axial Lead & Cartridge Fuses 3AB > Fast-Acting > 505 Series


Product Characteristics

Materials	Body : Ceramic Cap : Nickel–plated brass Leads : Tin-plated Copper
Terminal Strength	MIL-STD-202, Method 211, Test Condition A
Solderability	MIL-STD-202 Method 208
Product Marking	Cap1 : Brand logo, current and voltage ratings Cap2 : Series and agency approval marks

Operating Temperature:	–55°C to 125°C.
Thermal Shock:	MIL-STD-202, Method 107, Test Condition B (5 Cycles -65°C to +125°C).
Vibration	MILSTD-202, Method 201
Humidity	MIL-STD-202, Method 103, Test Condition A: High relative humidity (95%) and elevated temp (40°C) for 240 hours
Salt Spray	MIL-STD-202, Method 101, Test Condition B

Dimensions


Measurements displayed in millimeters (inches)



Packaging

Packaging Option	Packaging Specification	Quantity	Quantity & Packaging Code	Reel Size
505 Series				
Bulk	N/A	1000	MX	N/A
Bulk	N/A	1000	MXE	N/A
Bulk	N/A	1000	MX52LE	N/A

Part Numbering System



Recommended Accessories

Accessory Type	Series	Description	Max Application Voltage	Max Application Amperage
Holder	<u>150322</u>	In-Line Fuseholder	500	15
Block	<u>354</u>	Low Profile OMNI-BLOK® Fuse Block	600	30
359	<u>359</u>	High Current Screw Terminal Fuse Block	000	30
Clin	<u>122</u>	High Current Traditional PC Board Fuse Clip	1000	30
Clip 10	<u>101</u>	Rivet/Eyelet Type Fuse Clip	1000	15

Do not use in applications above rating.
 Please refer to fuseholder data sheet for specific re-rating information.

3. Please contact factory for applications greater than the max voltage and amperage shown.

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at: www.littelfuse.com/disclaimer-electronics.