

Sticklers™ Fiber Optic Splice & Connector Cleaner

Cleaning Fluid



Product Features:

- Fast evaporating, no residue optical grade cleaning fluid for cleaning fiber
- Not regulated for transport by land, sea or air
- Nonflammable, nontoxic
- Dissipates electrostatic charges
- Compliant with Ventura County Air Pollution Control District Rule 74.6; reference 74.6; B.2.C
- ROHS and REACH compliant






TYPICAL CLEANING APPLICATIONS:

- Pigtails and bare fibers for fusion splicing
- Ribbon fibers for mass fusion splicing
- Splicing plastic optical fibers and connectors
- Ceramic and composite ferrules
- Most glass and plastic photonic lenses
- Suitable cleaning fluid for tool kits



Patented Triton™ dispenser enables 3 cleaning methods

Video:
[How to Use Fiber Optic Splice & Connector Cleaner](#)
 @ SticklersCleaners.com

PACKAGING:	3 OZ (85 G) NET FLUID WEIGHT	10 OZ (284 G) NET FLUID WEIGHT
Part Number	MCC-POC03M 	MCC-POC10M
Cleans Per Can	650+	2500+
NSN #	6850-01-592-9391	N/A
Can Specifications	<ul style="list-style-type: none"> • 4.23 oz (120 g) total can weight • 1.54" OD x 5.12" H (39 mm OD x 130 mm H) 	<ul style="list-style-type: none"> • 13.2 oz (374 g) total can weight • 2.6" OD x 6.75" H (66 mm OD x 172 mm H)
Case Dimensions	8" L x 6" W x 6" H (203 mm L x 152 mm W x 152 mm H)	12" L x 9" W x 7" H (305 mm L x 229 mm W x 178 mm H)
Case Quantity	12 Cans per Case	12 Cans per Case
GHS/HCS Pictogram	Not Applicable	Not Applicable
Recycle Symbol		

Sticklers™ Fiber Optic Splice & Connector Cleaner conforms to the following Fiber Optic Industry Standards:



Industry Standards	Section	Description
ANSI/TIA 455-240 2009		Fiber Optic Connector End-Face Cleaning Evaluation
ANSI/TIA 568.3D-2016	E.3.5	Connector End-Face Cleaning
ARINC 805-4		Fiber Optic Test Procedures
ARINC 806-5		Fiber Optic Installation & Maintenance
AT&T ATT-TP-76461		Inspecting & Cleaning End-Faces
Cisco Systems Doc: 51837		Inspecting & Cleaning Procedures for Fiber Connectors
IBM SY27-2597-15		Cleaning End-Faces for Maintaining Fiber Links
IEC 61300-3-35	5.3	End-Face Cleaning
IEC 61627-1	7.8	Acceptable Wet-Dry End-Face Cleaning
IEC 62627-1	9.3	Procedure Wet-Dry Cleaning w/ Reel Type Cleaners
IEC 61627-1	9.4	Procedure Wet-Dry Cleaning w/ Sticks & Clickers
IPC 8497-1	7.3.6	Cleaning Fluids & West Swabs & Face Cleaning
IPC 8497-1	10	Minimizing Electrostatic Charge Effect
NASA-STD 8739.5A	8	Cleaning Workmanship Standards
SAE AIR6031		End-Face Cleaning
SAE ARP 6283	8.6	Approved Cleaning Solvents
SAE ARP 6283	9.1.1	Wet-Dry Cassette Cleaning
Telcordia GR2923 CORE Issue 2		End-Face Cleaning
Telcordia GR765-CORE	4.6	Fusion Splicing Materials & Consumables Criteria
Verizon VZ.TRP.9461	5.0	End-Face Cleaning

When You Need Perfectly Clean Splices & Connectors



SticklersCleaners.com



Follow Us!

MicroCare, LLC

595 John Downey Drive
New Britain, CT 06051 USA
Tel: +1 860 827 0626
Toll Free: 1 800 638 0125
Email: TechSupport@MicroCare.com

MicroCare Europe BVBA

Vekestraat 29 B11
Industriezone 't Sas
1910 Kampenhout, Belgium
Tel: +32 2 251 95 05
Email: EuroSales@MicroCare.com

MicroCare U.K. Ltd

Seven Hills Business Centre
South Street, Morley
Leeds, United Kingdom
LS27 8AT
Tel: +44 (0) 113 3609019
Email: mcceurope@microcare.com

MicroCare Asia Pte Ltd

102E, Pasir Panjang Road
Citilink, #05-06
Singapore 118529
Tel: +65 6271 0182
Email: TechSupport@MicroCare.sg